

MONICRON

Instructions

Connecting Up

Fit the two groups of 3.5mm plugs with colour spots as follows:

Yellow to tape EAR socket; white to tape MIC socket:

Red to computer EAR socket; Blue to computer MIC socket

Fit the 2.5mm plug (if fitted) to tape REMOTE socket.

Fit Monicron power plug to computer power socket; plug power supply into Monicron socket.

The LED will glow when slide switch is moved to the right.

OPERATING

LOADING PROGRAMS: Depress LOAD button then carry out the normal loading routine.

Ensure all other buttons are 'OFF', i.e. raised.

SAVING PROGRAMS: Depress SAVE button then carry out the normal save routine – all other buttons off.

MIC To record your voice on tape, set tape player to 'record' and depress MIC & SAVE buttons – all others 'off'.

Speak clearly @ 12 inches from Monicron.

REM Fitted to models without amplifier. Allows tape to run when raised or stop when depressed.

AMP Amplifies Spectrum. Depress AMP & SPKR buttons to operate, all others off.

SPKR Depress this button to hear contents of tape via Monicron speaker. Used to check loads, cue tape etc.

LEVEL METER Automatically monitors signal strength when loading. Is used to determine the optimum signal/volume level setting on tape player for your computer. When this level has been determined, individual tapes can be loaded at this level by adjusting the volume control. It may be necessary to run a 'dry' load to find the best setting.

IMPORTANT Do not attempt to operate the amplifier when loading; this may cause damage to the Monicron and/or computer. Do not attempt to open the sealed case; the Monicron comes complete and fully tested and any evidence of tampering with the sealed case is liable to invalidate the guarantee.

All the above functions are performed without disconnecting or swapping any leads.

We hope you enjoy using the Monicron; however, in the event of malfunction or other complaint, please return in a well padded envelope by recorded delivery.

DO NOT move the slide switch to 'OFF' whilst AMP&SPKR buttons are depressed, except momentarily.

Macquillan Electronics
72 Mere Road
Wigeton Magna
Leicester LE8 1RL. 811232

